

CP200 Series

Portable Two-way Radios



Motorola— a name you know and trust.

Motorola is a company of firsts with a rich heritage of innovation. We continue to invent what's next—connecting people, delivering mobility and making technology personal. Whether you need a simple yet reliable communication solution or a solution with enhanced functionality to organize multiple work groups, the CP200 Series of two-way radios help keep you and your team working efficiently. Featuring a lightweight, ergonomic design, powerful audio output and operation on both conventional and LTR trunking systems, the CP200 Series portable two-way radios help keep your work force connected. The result—increased productivity for your business.

Exceptional Durability

With superb durability, Motorola's radios are built to last. Motorola's rugged and reliable radios, undergo rigorous testing in the design process. We use U.S. Military Standards and Accelerated Life Testing, so you can be assured Motorola radios will hold up under demanding conditions. These tests are designed to simulate very harsh environments, including:

Rain—Steady rainfall and wind for 30 minutes on every surface.

Salt Fog—48 hours of exposure to an atomized salt solution.

Dust—6 hours of blowing dust on all surfaces.

Vibration—Up to 9 hours of exposure to vibration that simulates the rigors a radio could undergo while being transported.

Shock—18 shocks with a minimum G force of 40 Gs each.

Service Offerings

Even with the quality you have come to expect from Motorola, the every day use of your radios requires on-going maintenance to help ensure your radios are operating at peak performance. Managing the in-house repair and maintenance of your subscriber radios takes a dedicated staff of technicians, as well as an ongoing investment in diagnostic equipment, repair tools, and the technical training to keep up to speed on the latest technology. Motorola has made that investment and can help you easily and cost effectively keep your radios in top operating condition to ensure optimal efficiency and productivity. You can rely on Motorola to support your radio system with these Subscriber Repair service offerings:

Repair Service Advantage (RSA)

Repair Service Advantage is a post-warranty service offering that extends the service coverage of Motorola subscriber portable or mobile radios. RSA can be purchased as an option to new radio purchases and is available in 1, 2 or 3-year increments. (US only)

Extended Warranty

In addition to the 2-year standard warranty, Extended Warranty is available for a total of 3 or 5 year coverage. (Canada only)



CP200 portable two-way radio

The design and simple operation of the CP200 portable two-way radio makes it ideal for education, hospitality, retail, manufacturing and security organizations. This radio features a large, textured push-to-talk button, X-Pand™ technology for crisp, clear audio and two programmable buttons for quick access to frequently used features—all in a lightweight, durable design.



- Large Rotary Channel Selector
- Tricolor LED
- Rotary On/Off and Volume Control
- **Accessory Connector**
- Rugged, Die-Cast Chassis
- 3 Inch Spring Action Belt Clip Located on radio back
- Battery Latch Lock Located on radio bottom

All CP200 models include:

- Li-Ion 2250 mAh Battery
- · Rapid Rate Charger
- Antenna VHF Heliflex or UHF Whip
- 3 Inch Belt Clip
- Safety and Warranty Booklet
- · 2-Year Warranty

Features

CP200 Portable:

- 4/16 Conventional Channels
- Large Rotary Channel Selector Changes channels quickly and easily
- Rotary On/Off and Volume Control
- Tricolor LED Indicates radio status and battery levels
- Accessory Connector Convenient access for audio accessories
- 3 Inch Spring Action Belt Clip Attaches radio firmly to belt
- Rugged, Die-Cast Chassis With polycarbonate housing for greater protection

- · Large, Textured Push-to-Talk Button Easy to find and use, even when wearing
- Two Programmable Option Buttons Supports your choice of up to four product features
- · Privacy Codes Include: 42 standard TPL codes, 84 standard DPL codes and non-standard codes
- · System Scan and Auto Scan
- Single Priority Scan Frequently scans higher priority channel
- Battery Latch Lock Secures battery

- Quik-Call II[™] Signaling Call Alert Selective Call
- MDC 1200 Signaling Selective Radio Inhibit Radio Check

Selective Inhibit Push-to-Talk ID

- DTMF Signaling DTMF Push-to-Talk ID
- 2-year Standard Warranty

Programmable Features: Choose up to 4

- · Sticky Monitor/Monitor
- VOX
- Power Level

- Repeater/Talk Around
- Squelch

- Scan
- · Nuisance Channel Delete

CP200:XLS portable two-way radio

The expanded features of the CP200·XLS portable two-way radio makes it a perfect fit for education, hospitality, retail, manufacturing and security organizations who need additional capabilities and capacity to manage a large workforce. Featuring both conventional and LTR® trunking capability, the CP200·XLS enables you to efficiently organize your workforce. With both a limited keypad and full keypad model, the CP200·XLS also features an 8 character alpha-numeric display, four programmable buttons for quick access to up to eight programmable features and X-Pand™ technology for crisp, clear audio—all in a lightweight, durable design.



- Large Rotary Channel Selector Continuous rotary knob
- 128 Channels: Up to 100 LTR Talkgroups
- Backlit 8-Character Alphanumeric Display with user-friendly icons indicates radio status, battery levels and allows for viewing of channel names and Caller IDs
- Four Programmable Buttons: S1, S2, P1, P2
 Two side and two front buttons provide quick access to up to 8 features
- Menu Scroll Buttons Change channel and access menu features
- Full DTMF Keypad



All CP200 XLS portable models include:

- Li-Ion 2250 mAh Battery
- Rapid Rate Charger
- Antenna VHF Heliflex or UHF Whip
- 3 Inch Belt Clip
- Quick Reference/Safety and Warranty Guide
- 2-Year Warranty

CP200·XLS Limited and Full Keypad Portables:

- 128 Conventional Channels
- Up to 100 LTR Talkgroups
- Up to 10 Sites and 100 Talkgroups in LTR
- Mixed Assignment of Conventional Personalities and LTR Talkgroups
- Up to 20 Repeaters per Site in LTR
- Up to 4 Universal IDs per System in LTR
- Up to 40 Universal IDs per Radio in LTR
- Up to 8 Programmable Features
- Supports up to 16 Scan Lists of up to 16 Channels Per List - Limited Keypad only
- User-Editable Standard TPL/DPL Codes
- User-Editable Scan List
- Lights On/Off Keypad and display backlights

- Tones On/Off
- Call Tone Tagging

Tag a special tone for a particular call

Quik-Call II[™] Signaling Includes: Selective Call Encode: Calls a specific group or individual

Call Alert Encode: Notifies a specific group/ individual with an alert tone and lighted LED

- DTMF Signaling Includes:
- Selective Call/Call Alert Encode/Decode LTR Trunking Signaling Features:

MDC 1200 Signaling

PTT-ID Encode PTT-ID Decode

Radio Check Decode

Selective Radio Inhibit Decode Data-Operated Squelch (DOS) Pre-Time

The Full Keypad model has all of the same regular features as the Limited Keypad model plus the following:

- Dial Phone Numbers
- Manual Access Repeater Send DTMF tones to repeater
- User-Editable Phone List
- Speed Dial for Radio Call Encode

Programmable Features: Choose up to 8

Menu Mode

Access to the radio menu and the ability to select a menu option

- Monitor
 - Monitor radio traffic
- Repeater/Talkaround Toggle between using the repeater or
- transmitting directly to another radio **Revert Memory Channel** Instant access to the home channel/
- talkgroup Store Memory Channel

Store current channel/talkgroup to the home channel/talkgroup

- Home Revert Auto Key Keys up the radio and transmits an MDC
- PTT ID (LTR only) Voice Operated Transmission (VOX)
- Hands-free operation with an audio accessory

Keypad Lock/Unlock

Lock/unlock keypad to prevent unauthorized usage

Radio Call

Initiate Quik-Call II and/or DTMF Call Alert or Selective Call Encode from a call list

- Scan/Nuisance Channel/Talkgroup Delete Initiate or stop a scan and delete a nuisance channel/talkgroup while scanning
- Edit Scan List

Add, delete or prioritize channels / talkgroups

Phone Mode

Place and receive telephone calls through the repeater

Escalert

Increase the volume of the alarm tones when a radio call is not answered

Squelch

Toggle squelch level between tight and normal squelch

Power Level

Change transmit power between high and low power

Lights

Switch keypad and display backlights on or off

The Full Keypad model has all of the same programmable features as the Limited Keypad model plus the following:

- Speed Dial
- DTMF (Full-Keypad) Specific Features DTMF Last Number Redial in Phone Mode Auto DTMF Access/De-access Code Manual Entry of DTMF Access/ De-access Code

Motorola Original® accessories provide a custom communication solution.

Each Motorola Original accessory is performance-matched specifically to your CP200 and CP200·XLS radios; designed, built and tested to meet the same quality standards. They provide enhanced functionality, and exceptional reliability in real-life usage.

Audio Solutions

Earpieces and lightweight headsets provide comfortable and easy-to-wear solutions for long shifts—common in retail or hospitality environments. Temple Transducers are an innovative accessory that allows easy radio communication without blocking your external environment sounds. Medium-weight headsets provide durability and protection in more rugged and noisy environments. Surveillance Kits and the Ear Microphone System provide discreet options for security teams. Mag OneTM by Motorola accessories are a cost-effective solution for light-duty users.

Batteries

NiCD and NiMH batteries perform in more rugged environments, while Li-ion batteries provide a lightweight battery solution. For longer shifts or unusually heavy use, a high capacity Li-ion battery will provide extended talk time.

Chargers

Rapid and slow-rate chargers are available to meet specific charging needs. The rapid-rate charger will charge batteries within three hours, while the 10-hour charger can be used when overnight charging is convenient. A rapid-rate, multi-unit charger can charge up to six batteries at one time, while the multi-unit charger conversion kit allows you to convert your single-unit chargers into an efficient, cost-effective multi-unit charging station.

Carrying Accessories

You'd be surprised how much time can be saved when each user's radio is always in the same place—made easy by a versatile selection of carry accessories. *Leather and nylon carry cases* provide protection in rugged environments and are available in different sizes to support non-display and keypad models. *Chest packs and RadioPAks™* provide additional pouches for other on-the-job necessities.

For a complete listing of Motorola Original accessories and part numbers, please see the Accessory and Battery Catalog (RC-3-1008).







RLN5318



PMLN5003





NNTN4970

WPLN4161

PMMN4013

GENERAL SPECIFIC	CATIONS						
	CP200 VHF	CP200 UHF	CP200·XLS VHF	VHF CP200·XLS UHF			
Frequency	136-162 MHz 146-174 MHz	403-440 MHz 438-470 MHz 465-495 MHz	136-162 MHz 403-440 146-174 MHz 438-470 465-495				
Channel Capacity		6 Channels		128 Channels			
Power Supply	7.5 Vo	olts ± 20%	7.5 V	7.5 Volts ± 20%			
Dimensions with Battery 2250 mAh Li-Ion 1600 mAh Slim Li-Ion 1400 mAh NiMH 950 mAh NiCd	127.5 x 61.55 x 42mr 127.5 x 61.55 x 43mr	m (5.0 x 2.4 x 1.75 inches) m (5.0 x 2.4 x 1.65 inches) m (5.0 x 2.4 x 1.69 inches) m (5.0 x 2.4 x 1.75 inches)	127.5 x 61.50 x 45mm (5.0 x 2.4 x 1.75 inches) 127.5 x 61.55 x 42mm (5.0 x 2.4 x 1.65 inches) 127.5 x 61.55 x 45mm (5.0 x 2.4 x 1.65 inches) 127.5 x 61.55 x 45mm (5.0 x 2.4 x 1.75 inches)				
Weight with Battery 2250 mAh Li-Ion 1600 mAh Slim Li-Ion 1400 mAh NiMH 950 mAh NiCd	374 g 444 g	(13.04 oz) (13.19 oz) (15.66 oz) (14.98 oz)	370 g (13.04 oz) 374 g (13.19 oz) 444 g (15.66 oz) 425 g (14.98 oz)				
Average Battery Life ¹ 2250 mAh Li-Ion 1600 mAh Slim Li-Ion 1400 mAh NiMH 950 mAh NiCd	1W 5W 17 Hrs 14 Hrs 14 Hrs 12 Hrs 11 Hrs 10 Hrs 9 Hrs 8 Hrs	1W 4W 17 Hrs 14 Hrs 14 Hrs 12 Hrs 11 Hrs 10 Hrs 9 Hrs 8 Hrs	1W 5W 17 Hrs 14 Hrs 14 Hrs 12 Hrs 11 Hrs 10 Hrs 9 Hrs 8 Hrs	1W 4W 17 Hrs 14 Hrs 14 Hrs 12 Hrs 11 Hrs 10 Hrs 9 Hrs 8 Hrs			
FCC Designation	ABZ99FT3039 ABZ99FT3045	ABZ99FT4056 ABZ99FT4057 ABZ99FT4058	ABZ99FT3039 ABZ99FT4056 ABZ99FT3045 ABZ99FT4057 ABZ99FT4058				

RECEIVER SPECIFICATIONS								
	CP200 VHF		CP200 UHF		CP200·XLS VHF		CP200·XLS UHF	
Frequency	12.5 kHz	20/25/30 kHz ³	12.5 kHz	20/25/30 kHz ³	12.5 kHz	20/25/30 kHz ³	12.5 kHz	20/25/30 kHz ³
	136-162 MHz 146-174 MHz		403-440 MHz 438-470 MHz 465-495 MHz		136-162 MHz 146-174 MHz		403-440 MHz 438-470 MHz 465-495 MHz	
Sensitivity ² (12dB EIA SINAD)	0	.25 μV	0.25 μV		0.25µV		0.25μV	
Adjacent Channel Selectivity ²	-65 dB	-70 dB	-60 dB	-70 dB	-65 dB	-70 dB	-60 dB	-70 dB
Intermodulation ²	-70 dB	-70 dB	-70 dB	-70 dB	-70 dB	-70 dB	-70 dB	-70 dB
Frequency Stability ² (-30° to +60° C) 0.00025%		0.00025%		0.00025%		0.00025%		
Spurious Rejection ²	-5	75 dB	-75 dB		-75 dB		-75 dB	
nage and 1/2 I-F Rejection ² -70 dB		-70 dB		-70 dB		-70 dB		
Audio Output ² @ < 5% Distortion 500mW		500mW		500mW		500mW		

TRANSMITTER SPECIF	ICATIONS				
	CP200 VHF	CP200 UHF	CP200·XLS VHF	CP200·XLS UHF	
RF Output	1W / 5W	1W / 4W	1W / 5W	1W / 4W	
Frequency	136-162 MHz 146-174 MHz	403-440 MHz 438-470 MHz 465-495 MHz	136-162 MHz 146-174 MHz	403-440 MHz 438-470 MHz 465-495 MHz	
Channel Spacing	12.5/2	0/25 kHz ³	12.5/20/25 kHz ³		
Frequency Stability (-30° to +60° C)	0.0	0.00025%			
Spurs/Harmonics ²	-36 dBm < 1 GH	z, -30 dBm > 1 GHz	-36 dBm < 1 GHz, -30 dBm > 1 GHz		
Audio Response ² From 6dB/octave Premphasis, 300 to		, -3 dB	+1, -3 dB		
Audio Distortion2 ² @ 1000 Hz, 60% Rated Maximum De	eviation	< 3%			
FM Noise ²		(12.5 kHz) (25 kHz) ³	-40 dB (12.5 kHz) -45 dB (25 kHz) ³		
FCC Modulation 20/25/30 kHz ³ 12.5 kHz	16KOF3E 11KOF3E	16KOF3E 11KOF3E	16KOF3E 11KOF3E	16KOF3E 11KOF3E	

PORTABLE MILITARY STANDARDS 810 C, D, E and F								
	MIL-STD 810C		MIL-STD 810D		MIL-STD 810E		MIL-STD 810F	
	Method	Procedures	Method	Procedures	Method	Procedures	Method	Procedures
Low Pressure	500.1		500.2	II	500.3	II	500.4	I
High Temperature	501.1	l, II	501.2	1, 11	501.3	l, II	501.4	1, 11
Low Temperature	502.1		502.2	I, II	502.3	I, II	501.4	I, II
Temperature Shock	503.1	I	503.2		503.3		503.4	1
Solar Radiation	505.1	I	505.2		505.3	I	505.4	
Rain	506.1	I, II	506.2	1, 11	506.3	I, II	506.4	
Humidity	507.1	II	507.2	II, III	507.3	II, III	507.4	III
Salt Fog	509.1	I	509.2		509.3	I	509.4	
Blowing Dust	510.1	I	510.2		510.3	I	510.4	
Vibration	514.2	VIII, X	514.3	I	514.4	1	514.5	
Shock	516.3	I, II, V	516.3	I, IV	516.4	I, IV	516.5	

ENVIRONMENTAL	
Operating Temperature	-30° to +60° C
Storage Temperature	-40° to +85° C
ESD	IEC 801-2 KV
Thermal Shock	-40° to +80° C
Humidity	95% RH @ 8 Hour
Water and Dust Intrusion	IP 54
Dealine Test	lean a at to a t

Accelerated Life Test

Motorola's Accelerated Life Test (ALT) is a developmental process of rigorous laboratory testing that simulates years of field use. Motorola has a firm commitment to quality and reliability. These radios have been designed, manufactured and tested to achieve high levels of component and workmanship quality. Motorola radios are designed to minimize costly repairs and downtime.

¹ 5% receive, 5% transmit, 90% standby.

² All electrical specifications and methods refer to EIA/TIA 603 standards. Specifications shown are typical and subject to change without notice.

 $^{^{\}rm 3}$ 25 kHz not available in the US on new equipment after 1/1/2011.





Motorola, Inc. 1301 East Algonquin Road Schaumburg, Illinois 60196

MOTOROLA and the Stylized M Logo are registered in the US Patent & Trademark Office. All other product or service names are the property of their respective owners.
© Motorola, Inc. 2010. All rights reserved.